

### **GS-MPI004 HD Configuration options.**

Hold the \* and power up.

Signal LED and sounder LED will flash to indicate that you are in configuration mode.

#### Key functions

0	Load factory defaults	
1	Auto switching from 2G to 3G	3G LED will flash
2	2G only	3G LED OFF
3	3G only	3G LED ON
4	Echo canceller ON	Off hook LED ON
5	Echo canceller OFF	Off hook LED OFF
6	Noise suppressor ON	On hook LED ON
7	Noise suppressor OFF	On hook LED OFF
8	Peak compressor ON	Batt LED ON
9	Peak compressor OFF	Batt LED OFF
*	Used to enter menu at power up	
#	Exit menu	REBOOT REQUIRED

After making changes the MPI004 HD **MUST** be power cycled.