

PELTOR Ear defending headsets – Wiring Information

54-380 - PELTOR MT7H79A HEADSET Ear defending, stereo, unterminated

54-384 - PELTOR MT7H61FA HEADSET Ear defending, stereo, unterminated

54-376 - PELTOR MT7H79/61A HEADSET Ear defending, stereo, unterminated

Wiring Colour Code:	Yellow	Mic	Ground
	Black	Mic	+
	Red	LH Ear	–
	White	LH Ear	+
	Green	RH Ear	–
	Brown	RH Ear	+

Note:

There have been 5 core variants on the market.

Cables missing the brown insulated core are wired thus:-

Yellow	Mic	Ground
Black	Mic	+
Red	LH Ear – & RH Ear –	
White	LH Ear +	
Green	RH Ear +	

54-381 - PELTOR MT7H79A HEADSET Ear defending, with 4 pole 7mm plug

54-385 - PELTOR MT7H61FA HEADSET Ear defending, with 4 pole 7mm plug

54-377 - PELTOR MT7H79/61A HEADSET Ear defending, with 4 pole 7mm plug

Connector Wiring:	Sleeve	Mic	Ground
	Ring 2	Mic	+
	Ring 1	RH Ear + & LH Ear –	
	Tip	RH Ear – & LH Ear +	



PELTOR Ear defending headsets – Wiring Information

54-382 - PELTOR MT7H79A HEADSET Ear defending, with 4 pin female XLR

54-386 - PELTOR MT7H61FA HEADSET Ear defending, with 4 pin female XLR

54-378 - PELTOR MT7H79/61A HEADSET Ear defending, with 4 pin female XLR

Connector Wiring:	Pin 1	Mic	Ground
	Pin 2	Mic	+
	Pin 3	RH Ear - & LH Ear –	
	Pin 4	RH Ear + & LH Ear +	

54-3882 PELTOR MT7H79A HEADSET Ear defending, with 5 pin male XLR

54-3883 PELTOR MT7H61FA HEADSET Ear defending, with 5 pin male XLR

54-3881 PELTOR MT7H79/61A HEADSET Ear defending, with 5 pin male XLR

Connector Wiring:	Pin 1	Mic	Ground
	Pin 2	Mic	+
	Pin 3	RH Ear - & LH Ear –	
	Pin 4	LH Ear +	
	Pin 5	RH Ear +	