# Product Information Sheet

## NEUTRIK NADITBNC-FX

**49-172** NEUTRIK NADITBNC-FX



### DESCRIPTION

Female XLR cable type connector 110 Ω input - female BNC 75 Ω output.

For matching balanced 110 ohm digital audio circuits to unbalanced 75 ohm video circuits.

### FEATURES & BENEFITS

Allow long cable runs for digital audio signals via low attenuation coax lines

Match balanced to coaxial lines

Match impedances 110 Ω to 75 Ω

Simple to use, passive units

### TECHNICAL SPECIFICATION

| | | | |
|---|---|---|---|
| **Product** | NADITBNC-FX | **VSWR** | < 1.1 |
| **Connection** | Type Adapter Female Cable type XLR to Female BNC | **Return loss** | > 26.4 dB |
| **Frequency range** | 0.1 - 6 MHz | **Insertion Loss** | < 0.3 dB @ 0.1 MHz to 10 MHz |
| **Rated voltage** | ≤ 5 V p-p | | |

